

# Delock Audio Converter Digital > Analogue

## Description

The audio converter by Delock converts a digital audio signal into an analogue stereo signal. For example a DVD or Blu-ray player can be connected to the input of the device and the signal can be supplied via optical TOSLINK or via S/PDIF coaxial connection. At the output port, the audio signal is transmitted via the RCA connection.



**Item no. 62444**

EAN: 4043619624447

Country of origin: China

Package: White Box

## Technical details

- Connectors:
  - Input:
    - 1 x TOSLINK female S/PDIF
    - 1 x Coaxial female S/PDIF
    - 1 x DC jack
  - Output:
    - 2 x RCA female
- Supported sample rates: 32 / 44.1 / 48 / 96 kHz
- Robust metal housing
- Dimensions (LxWxH): ca. 63 x 41 x 21 mm

## Power supply specification

- Wall power supply
- Input: AC 100 ~ 240 V / 50 ~ 60 Hz / 0.3 A
- Output: 5 V / 1 A
- Ground outside, plus inside
- Dimensions:
  - inside: ø ca. 2.1 mm

outside:  $\varnothing$  ca. 5.5 mm  
length: ca. 9 mm

---

## System requirements

- Digital audio signal
- Connection cable


---

## Package content

- Converter digital > analogue
- Power supply
- User manual

---

## Images



### Interface

Output:	2 x RCA female (red, white)
Input:	1 x Coaxial female S/PDIF 1 x TOSLINK female S/PDIF 1 x 5 V DC female 5,5 mm x 2,1 mm

### Physical characteristics

Housing colour:	black
Housing material:	Plastic
Length:	63 mm
Width:	41 mm
Height:	21 mm