

Delock DisplayPort KVM Switch 2 > 1 s USB 2.0-om i audioulazom

Opis

Ova KVM sklopka tvrtke Delock prikladna je za spajanje dvaju računala s DisplayPort izlazom na jedan DisplayPort monitor i / ili jedan HDMI monitor. Gumbom ili daljinskim upravljačem možete prebacivati između oba računala. Postoje i izlazi DisplayPort i HDMI za spajanje dvaju monitora, od kojih samo jedan može biti aktivan istovremeno. Nadalje, tri USB Tipa-A ulaza mogu se koristiti za spajanje miša, tipkovnice, tvrdog diska ili USB memorije. Ugrađena funkcija za USB slušalice omogućava vam korištenje slušalica i mikrofona na oba računala.

Napomena

KVMs emulate a standard wired 104 key keyboard and wired generic 2 or 3 button scroll wheel mouse on their respective console ports. Whether or not a wireless or gaming mouse and keyboard work with KVM switches depends on several factors; in general, most wireless mice and keyboards do not support working with KVM switches. We recommend to use a standard wired mouse and keyboard with our KVM switches.



Predmet br. 11367

EAN: 4043619113675

Zemlja podrijetla: China

Pakiranje: Retail Box

Tehnički podaci

- Priključak:

Ulaz:

2 x DisplayPort 20-polni ženski

2 x USB 2.0 Tipa-B, ženski

1 x 9-pinski D-Sub, ženski

1 x DC 5 V priključak za napajanje

1 x 3,5 mm stereo priključak ženski 3 kontakta za dodatni IC-prijamnik

Izlaz:

1 x DisplayPort 20-polni ženski

1 x HDMI-A 19-polni ženski

3 x USB 2.0 Tip-A, ženski

2 x 3,5 mm ženski stereo priključak s 3 kontakta

- 2 gumba s LED indikatorom izvora (PC1, PC2) i utorom (DisplayPort, HDMI)
- Prebacivanje putem gumba ili infracrvenog daljinskog upravljača
- Podaci za DisplayPort 1.1a
- DisplayPort izlaz:
Razlučivost 2560 x 1440 @ 60 Hz / 3840 x 2160 @ 30 Hz (ovisno o sustavu i spojenom hardveru)
- HDMI / DP++ izlaz:
Razlučivost 1920 x 1080 @ 60 Hz (ovisno o sustavu i spojenom hardveru)
- DisplayPort izlaz podržava dvojni način rada DP++
- Konfiguracija i upravljanje uređajem preko RS232 sučelja
- čvrsto metalno kućište
- Boja: crno
- Mjere (DxŠxV): oko 257 x 112 x 33 mm
- Neovisan o operativnom sustavu, nije potrebna instalacija upravljačkog programa

Podaci o električnom napajanju

- Napajanje iz zidne utičnice
- Ulaz: AC 100 ~ 240 V / 50 ~ 60 Hz / 0,35 A
- Izlaz: 5 V / 2 A
- Uzemljenje izvana i iznutra
- Mjere:
iznutra: \varnothing oko 2,1 mm
izvana: \varnothing oko 5,5 mm
duljina: oko 9 mm

Preduvjeti sustava

- Računalo s Mini DisplayPort ulazom ženski + USB Tip-A ženski
- Monitor ili TV s Mini DisplayPort ili HDMI sučelje

Sadržaj pakiranja

- KVM preklopnik s USB i audio funkcijom
- 2 x kabel USB A muški na USB B muški, duljina oko 1 m
- 2 x kabel DP muški na Mini DP ženska, duljina oko 0,9 m
- 2 x Mini kabel DP muški prema DP muškom, duljina oko 0,9 m
- Vanjski izvor napajanja
- Daljinski upravljač
- Korisnički priručnik

Slike



Interface

| | |
|--------|---|
| Izlaz: | 1 x DisplayPort ženski 1 x HDMI-A ženski 2 x 3.5 mm stereo jack female (speaker, microphone) 3 x USB 2.0 Tipa-A ženski |
| Ulaz: | 1 x 3,5 mm ženski stereo priključak s 3 kontakta 1 x 5 V DC female 5,5 mm x 2,1 mm 2 x DisplayPort ženski 2 x USB 2.0 Tipa-B, ženski |

Technical characteristics

| | |
|----------------------------|--|
| Maximum screen resolution: | 3840 x 2160 @ 30 Hz 2560 x 1440 @ 60 Hz |
|----------------------------|--|

Physical characteristics

| | |
|--------------------|---------|
| Kućište boja: | crne |
| Materijal kućišta: | metal |
| Duljina: | 25.7 cm |
| Width: | 11,2 cm |
| Height: | 3,3 cm |